

(1) **EC-TYPE EXAMINATION CERTIFICATE**

(2) **Equipment and protective systems intended for use in potentially explosive atmospheres - Directive 94/9/EC**

(3) EC-Type Examination Certificate Number: **KEMA 08ATEX0070** Issue Number: 1

(4) Equipment: **Signal Converter Type VersaFlow TWM 9000 F**

(5) Manufacturer: **Honeywell International, HFS**

(6) Address: **512 Virginia Drive, Fort Washington, PA 19034, USA**

(7) This equipment and any acceptable variation thereto is specified in the schedule to this certificate and the documents therein referred to.

(8) KEMA Quality B.V., notified body number 0344 in accordance with Article 9 of the Council Directive 94/9/EC of 23 March 1994, certifies that this equipment has been found to comply with the Essential Health and Safety Requirements relating to the design and construction of equipment and protective systems intended for use in potentially explosive atmospheres given in Annex II to the directive.

The examination and test results are recorded in confidential test report number 2113920-1.

(9) Compliance with the Essential Health and Safety Requirements has been assured by compliance with:

EN 50014 : 1997 + A1, A2
EN 50020 : 2002

EN 50018 : 2000 + A1
EN 50281-1-1 : 1998 + A1

EN 50019 : 2000
EN 50284 : 1999

(10) If the sign "X" is placed after the certificate number, it indicates that the equipment is subject to special conditions for safe use specified in the schedule to this certificate.

(11) This EC-Type Examination Certificate relates only to the design, examination and tests of the specified equipment according to the Directive 94/9/EC. Further requirements of the directive apply to the manufacturing process and supply of this equipment. These are not covered by this certificate.

(12) The marking of the equipment shall include the following:



II 2 (1) GD or II 2 GD EEx de [ia] IIC T6 T 85 °C

This certificate is issued on June 11, 2008 and, as far as applicable, shall be revised before the date of cessation of presumption of conformity of (one of) the standards mentioned above as communicated in the Official Journal of the European Union.

KEMA Quality B.V.


P.T. van Nijen
Certification Manager





(13) **SCHEDULE**

(14) **to EC-Type Examination Certificate KEMA 08ATEX0070**

Issue No. 1

(15) **Description**

The Signal Converter Type VersaFlow TWM 9000 F, when connected to a suitable certified electromagnetic flowmeter primary head, is used for measuring, counting and displaying the linear flow of an electrically conductive liquid and consists of a support bracket and a signal converter housing, with an electronics unit and a terminal compartment.

Depending on the electronics unit used, several signal output options like a 4 - 20 mA current signal, a fieldbus connection, pulse and status signals are available. The output signals are either intrinsically safe or non intrinsically safe.

The support bracket contains the field connection box with separated terminals for the field coil wiring in type of protection increased safety "e" and the electrode wiring in type of protection intrinsic safety "i".

The maximum surface temperature of the enclosure T 85 °C is based on an ambient temperature of 65 °C.

Ambient temperature range: -40 °C to +60 °C (stainless steel housing)

Ambient temperature range: -40 °C to +65 °C (aluminium housing)

The degree of protection of the apparatus enclosure is IP64 according to EN 60529.

Electrical data

Power supply 100 - 230 Vac -15/+10 %, 22 VA
 (terminals L, N or L+, L-) 12 - 24 Vdc -25/+30 %, 12 W
 24 Vac -15/+10 %, 22 VA
 24 Vdc -25/+30 %, 12 W
 $U_m = 253 V$

Intrinsically safe I/O signal circuits

In type of protection intrinsic safety EEx ia IIC, only for connection to a certified intrinsically safe circuit, with the maximum values per circuit per table below:

Type of PCB	Type of I/O circuit (terminals)	U_o [V]	I_o [mA]	P_o [W]	C_o [nF]	L_o [mH]
Ex i IO	4 - 20 mA with HART active (C and C-)	21	90	0,5 note 1	90	2,0
					110	0,5
Ex i Option	4 - 20 mA active (A and A-)	21	90	0,5 note 1	90	2,0
					110	0,5



(13) **SCHEDULE**

(14) **to EC-Type Examination Certificate KEMA 08ATEX0070**

Issue No. 1

Type of PCB	Type of I/O circuit (terminals)	U_i [V]	I_i [mA]	P_i [W]	C_i [nF]	L_i [μ H]
Ex i IO	4 - 20 mA with HART passive (C and C-)	30	100	1,0	10	0
	pulse/status output (D and D-)					
Ex i Option	4 - 20 mA passive (A and A-)	30	100	1,0	10	0
	pulse/status output / control input (B and B-)					
Fieldbus IO note 2	Profibus-PA (C, C-, D and D-)	24	380	5,32	5	10

note 1: linear characteristic

note 2: the fieldbus circuit complies with the FISCO model according to IEC 60079-27.

Non-intrinsically safe I/O signal circuits

(terminals A, A-, A+, B, B-, C, C-, D and D-) $U_n \leq 32$ Vdc, $I_n \leq 100$ mA

Field coil circuit
(terminals 7, 8, 9)

For connection to an associated certified primary head
 $U \leq 40$ V (pulsed)
 $I \leq 125$ mA (fuse protected)

Electrodes circuit
(terminals 1, 2, 20, 3, 30, 4, 40)

in type of protection intrinsic safety EEx ia IIC,
with the following maximum values:

- $U_o = 14$ V
- $U_{I_o} = 70$ mA
- $P_o = 300$ mW linear characteristic
- $C_o = 430$ nF
- $L_o = 2$ mH

Installation instructions

When used in a potentially explosive atmosphere, requiring the use of apparatus of equipment category 2G, certified cable entry devices shall be used that are suitable for the application and correctly installed.

When used in a potentially explosive atmosphere, requiring the use of apparatus of equipment category 2D, certified cable entry devices with a degree of ingress protection of at least IP6X according to EN 60529 shall be used that are suitable for the application and correctly installed.

Unused openings shall be closed with suitable certified closing elements.

With the use of conduit, a suitable certified sealing device such as a stopping box with setting compound shall be provided immediately at the entrance to the flameproof enclosure.

(13) **SCHEDULE**

(14) **to EC-Type Examination Certificate KEMA 08ATEX0070**

Issue No. 1

To avoid voltage and current addition the intrinsically safe circuits shall be separated and wired according to EN 60079-14.

Routine tests

Routine tests according to EN 50018 are not required for the signal converter housing since the overpressure test has been carried out at four times the reference pressure.

Electric strength tests according to EN 50019 Clause 6.1 shall be applied during one minute without breakdown as follows:

- On each terminal compartment in type of protection increased safety "e" with 1500 V between the power supply circuit and the enclosure and with 500 V between the signal in- and output circuits and the enclosure.
- On each field connection box with 500 V between the field coils circuit and the enclosure and with 1500 V between the field coils circuit and the intrinsically safe sensor circuit.

(16) **Test Report**

KEMA No. 2113920-1.

(17) **Special conditions for safe use**

None.

(18) **Essential Health and Safety Requirements**

Covered by the standards listed at (9).

(19) **Test documentation**

As listed in Test Report No. 2113920-1.